

Exercise session 5

Internal Stability of LFT. Structured Singular Value μ . Structured Robust Stability and Performance. μ Synthesis via $D - K$ iterations.

Reading Assignment

Read [Zhou] Ch. 10. Optional reading:

- Stability Theory for LFT — [Francis] Ch. 3,4, [Zhou] Ch. 11.
- μ — [Skogestad,Postlethwaite] Ch. 8.7–8.14 (Many examples!!!).

Exercises

E5.1 [Zhou] 10.1

E5.2 [Zhou] 10.4

E5.3 [Zhou] 10.9

E5.4 Consider a system P and a controller K

$$P(s) = \frac{1}{75s + 1} \begin{pmatrix} -87.8 & 1.4 \\ -108.2 & -1.4 \end{pmatrix}, \quad K(s) = \frac{75s + 1}{s} \begin{pmatrix} -0.0015 & 0 \\ 0 & -0.075 \end{pmatrix}$$

and a diagonal uncertainty $\Delta = \text{diag}\{\delta_1, \delta_2\}$.

- With the help of Robust Toolbox calculate $\mu_\Delta(T)$ ($= \min_D \|DTD^{-1}\|$. Why?) and $\|T\|$ at the frequency $\omega_0 = 0.2$ for $T = KP(I + KP)^{-1}$. Estimate the conservatism.
- Analyze $T(j\omega_0)$ and $D_{\min}T(j\omega_0)D_{\min}^{-1}$ and indicate the property that you think most contributes to this difference.
- Assume the multiplicative uncertainty model

$$P_\Delta = P(I + W\Delta), \quad W(s) = \frac{s + 0.2}{0.5s + 1}, \quad \|\Delta\|_\infty < 1$$

and the performance criterion to be

$$\|W_p(I + P_\Delta K)^{-1}\|_\infty \leq 1, \quad W_p(s) = \frac{s + 0.1}{2s}.$$

1. Test stability robustness ignoring the structure of Δ .
2. Test stability robustness taking into account the structure of Δ .
3. Test nominal performance.
4. Test robust performance taking into account the structure of Δ .

Hand-In problems:**H5.1** [Zhou] 10.3**H5.2** Consider a stable nominal plant P and an uncertainty model

$$P_\Delta = (I + W_1\Delta_1)P + W_2\Delta_2, \quad \|\Delta_i\|_\infty < 1.$$

The robust performance objective is to achieve

$$\|W_3(I + P_\Delta K)^{-1}\|_\infty \leq 1$$

for all P_Δ .

- (a) Make a block diagram for the closed loop system showing all weights and uncertain blocks.
- (b) Pull out all uncertainties and redraw the block diagram as upper LFT for uncertainties and lower LFT for K with respect to a generalized plant G . Determine the generalized plant G .
- (c) Close G by K and find the resulting closed loop function M (in terms of LFT).
- (d) Give a condition for stability robustness, ignoring the structure of Δ .
- (e) Give a condition for stability robustness, taking into account the structure of Δ .
- (f) Repeat last item for robust performance.
- (g) Under condition that the plant is SISO find the analytical expressions for robust stability and robust performance.